


## Octal Sockets:

8-pin



P/N: OT08PC

8-pin 35mm DIN rail or surface mount octal socket. OT08PC is rated at 10A @ 600VAC and has pressure clamp terminals. For use with AWG 12 to 22 (3.2 to 0.33 mm<sup>2</sup>) wire sizes.

P/N: NDS-8

8-pin 35mm DIN rail or surface mount octal socket. NDS-8 is rated at 10A @ 300VAC. Surface mounted with two #6 (M 3.5 x 0.6) screws or snaps onto a 35 mm DIN rail. A spring mechanism allows easy removal. Screw terminals with captive wire clamps accept up to two #14 AWG (2.45 mm<sup>2</sup>) wires. Uses P5C8 hold-down clips.




P/N: P1011-6

8-pin surface mount socket with binder head screw terminals. Rated 10A @ 600VAC. When used with TDM, TDB, TDS Series timers the combination is UL Listed. Uses P5C8 hold-down brackets.

## Magnal Sockets:

11-pin




P/N: OT11PC

11 pin 35mm DIN rail or surface mount socket. OT11PC is rated at 10A @ 300VAC and has pressure clamp terminals. For use with AWG 12 to 22 (3.2 to 0.33 mm<sup>2</sup>) wire sizes.

P/N: NDS-11

11 pin 35 mm DIN rail or surface mount socket. OT11PC is rated at 10A @ 300VAC. Surface mounted with two #6 (M 3.5 x 0.6) screws or snaps onto a 35 mm DIN rail. A spring mechanism allows easy removal. Screw terminals with captive wire clamps accept up to two #14 AWG (2.45 mm<sup>2</sup>) wires. Uses P5C11 hold-down clips.



## Hold-down Clips:

P/N: P5C8 or P5C11


Securely mounts plug in controls in any position. Also provides protection against vibration. Select the P5C8 for use with NDS-8, or the P5C11 for use with NDS-11 sockets. Comes in sets of two.



## Hold-down Brackets:

P/N: P5C8B8

Designed for use with P1011-6 socket. Securely mounts 8-pin plug-in controls in any position, and provides protection against vibration. Sold in pairs.



## Front Panel Mount Kit:

P/N: BZ1

Provides an easy method of through-the-panel mounting of 8 or 11-pin plug-in timers, flashers, and other controls. May be mounted in panels up to 0.125 in. (3.2mm) thick. Includes two clamps and two screws.

