

### 3-pole contactors

AF40 ... AF96



AF40-30-11



AF80-30-11

**18.5 to 30 kW - AC / DC operated with 1 N.O. + 1 N.C. auxiliary contacts**

IEC		UL / CSA		Rated control circuit voltage		Auxiliary contacts fitted		Type	Order code	Weight Pkg (1 pce)
Rated operational power	current	3-phase motor rating	General use rating	Uc min. ... Uc max.						
400 V	$\theta \leq 40^\circ\text{C}$	480 V	600 V AC	V 50/60 Hz	V DC					kg
AC-3	AC-1									
kW	A	hp	A							
185	70	30	60	24...60	20...60 <sup>1</sup>	1	1	AF40-30-11-11	1SBL347001R1111	1.010
				48...130	48...130	1	1	AF40-30-11-12	1SBL347001R1211	1.010
				100...250	100...250	1	1	AF40-30-11-13	1SBL347001R1311	0.990
				250...500	250...500	1	1	AF40-30-11-14	1SBL347001R1411	0.990
22	100	40	80	24...60	20...60 <sup>1</sup>	1	1	AF52-30-11-11	1SBL367001R1111	1.010
				48...130	48...130	1	1	AF52-30-11-12	1SBL367001R1211	1.010
				100...250	100...250	1	1	AF52-30-11-13	1SBL367001R1311	0.990
				250...500	250...500	1	1	AF52-30-11-14	1SBL367001R1411	0.990
30	105	50	90	24...60	20...60 <sup>1</sup>	1	1	AF65-30-11-11	1SBL387001R1111	1.010
				48...130	48...130	1	1	AF65-30-11-12	1SBL387001R1211	1.010
				100...250	100...250	1	1	AF65-30-11-13	1SBL387001R1311	0.990
				250...500	250...500	1	1	AF65-30-11-14	1SBL387001R1411	0.990
37	125	60	105	24...60	20...60 <sup>1</sup>	1	1	AF80-30-11-11	1SBL397001R1111	1.260
				48...130	48...130	1	1	AF80-30-11-12	1SBL397001R1211	1.260
				100...250	100...250	1	1	AF80-30-11-13	1SBL397001R1311	1.210
				250...500	250...500	1	1	AF80-30-11-14	1SBL397001R1411	1.210
45	130	60	115	24...60	20...60 <sup>1</sup>	1	1	AF96-30-11-11	1SBL407001R1111	1.260
				48...130	48...130	1	1	AF96-30-11-12	1SBL407001R1211	1.260
				100...250	100...250	1	1	AF96-30-11-13	1SBL407001R1311	1.210
				250...500	250...500	1	1	AF96-30-11-14	1SBL407001R1411	1.210

<sup>1</sup>For control by PLC-output, use RA4 interface relay.